

LHM 0606/10 Ceiling Loudspeaker



- ► Suitable for speech and music reproduction
- ► Flush-mounting in ceiling cavity
- ► Easy to install
- ► Simple power setting
- Optional certified fire dome mounting
- ► Unobtrusive in virtually all interiors
- Complies with international installation and safety regulations

The LHM 0606/10 is a general purpose, 6 W, cost-effective ceiling loudspeaker. It is clamp mounted into the ceiling. An optional fire dome is available.

Functions

An economic flushing-mounting ceiling loudspeaker is available for general purpose applications. This full range loudspeaker is suitable for both speech and music reproduction in shops, department stores, schools, offices, sports halls, hotels and restaurants.

The speaker assembly consists of a single-piece, 6W dual cone loudspeaker and frame, with a 100 V, matching transformer mounted on the back. A circular metal grille is an integrated part of the front. The appearance and neutral white color has been selected to be unobtrusive in virtually all interiors.

Certifications and Approvals

All Bosch loudspeakers are designed to withstand operating at their rated power for 100 hours in accordance with IEC 268-5 Power Handling Capacity (PHC) standards. Bosch has also developed the Simulated Acoustical Feedback Exposure (SAFE) test to demonstrate that they can withstand two times their rated power for short durations. This ensures extra reliability under extreme

conditions, leading to higher customer satisfaction, longer operating life, and much less chance of failure or performance deterioration.

Safety acc. to EN 60065


Installation/Configuration Notes

Mounting

The assembly is simply and quickly installed into a hole in the ceiling cavity. It is secured by two integral spring-loaded ceiling locking clamps. A circular template for marking a 165 mm diameter hole is included with the loudspeaker. Three lead wires on the matching transformer (primary) provide selection of nominal full-power, half-power or quarter-power radiation.


Fire dome

During a fire, the ceiling cavity in which loudspeakers are installed can allow flames to spread throughout a building. To prevent fire entering the caving via the loudspeaker, the ceiling loudspeaker can be fitted with a protective steel fire dome LBC 3080/01. This optional fire dome is mounted on the loudspeaker assembly using four self-tapping screws, supplied as standard. There are four knock-out holes; two (2) for rubber grommets (supplied) and two (2) for cable glands. (PG13).







Dimensions in mm



Circuit diagram




Frequency response



Polar diagram (measured with pink noise)

LBC 3080/01 Fire Dome (optional)





LHM 0606/10 + LBC 3080/01 Fire dome assembly dimensions in mm

Technical Specifications

Electrical

Maximum power	9 W
Rated power	6/3/1.5W
Sound pressure level at 6 W / 1 W (1 kHz, 1 m)	92 dB/ 84 dB (SPL)
Effective frequency range (-10 dB)	80 Hz to 18 kHz
Opening angle at 1 kHz/4 kHz (-6 dB)	175° / 55°
Rated voltage	100 V
Rated impedance	1667 ohm
Connector	Flying leads

Mechanical

Diameter	199 mm (7.8 in)
Maximum depth	70.5 mm (2.8 in)
Mounting cut-out	165 + 5 mm (6.5 + 0.20 in)
Speaker diameter	152.4 mm (6 in)
Weight	620 g (1.37 lb)
Color	Off-white (RAL 9010)

Environmental

Operating temperature	-25 °C to +55 °C (-13 °F to +131 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

LBC 3080/01 Fire Dome

Diameter	147 mm (5.8 in)
Max depth	87 mm (3.4 in)
Certified B15	acc. to DIN 4102
Color	White (RAL 9010)
Weight	360 g (0.79 lb)

Ordering Information	
LHM 0606/10 Ceiling Loudspeaker	LHM 0606/10
Accessories	
LBC 1256/00 EVAC Connection Adapter 3-pole screw connector, 100 pieces	LBC 1256/00

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com